
































Ulanzi BS004 Power Bank																					
SKU	BS004																				
Product Images																					
Key Fetures	<ol style="list-style-type: none"> 1. Conveniently mounted on a tripod, or on a camera 2. Power and charge a variety of photographic equipment 3. Built-in 1/4, 3/8 interface, directly mounted on the camera, tripod, lighting and other equipment 4. Full-colour display, easy to accurately and timely check the power status 5. DC adjustable voltage output 																				
Main Parameters	<table border="1"> <tr> <td>Battery Capacity</td> <td>4800mAh*4=19200mAh 71.04Wh</td> </tr> <tr> <td>Rated capacity (output capacity)</td> <td>10600mAh (5V3A)</td> </tr> <tr> <td>Screen</td> <td>1.14 inch full colour screen</td> </tr> <tr> <td>Buttons</td> <td>Up, Down, Left, Right, Centre 5 buttons</td> </tr> <tr> <td>Working Temperature</td> <td>Charging 0~40 degrees Celsius, Discharging</td> </tr> <tr> <td>Life Cycles</td> <td>>300 times</td> </tr> <tr> <td>Weight</td> <td>520g</td> </tr> <tr> <td>Input</td> <td>Type-C1, DC</td> </tr> <tr> <td>Output</td> <td>Type-C1, Type-C2, USB-A, DC</td> </tr> <tr> <td>Simultaneous charging and discharging</td> <td>Support, prioritise mobile phone charging</td> </tr> </table>	Battery Capacity	4800mAh*4=19200mAh 71.04Wh	Rated capacity (output capacity)	10600mAh (5V3A)	Screen	1.14 inch full colour screen	Buttons	Up, Down, Left, Right, Centre 5 buttons	Working Temperature	Charging 0~40 degrees Celsius, Discharging	Life Cycles	>300 times	Weight	520g	Input	Type-C1, DC	Output	Type-C1, Type-C2, USB-A, DC	Simultaneous charging and discharging	Support, prioritise mobile phone charging
Battery Capacity	4800mAh*4=19200mAh 71.04Wh																				
Rated capacity (output capacity)	10600mAh (5V3A)																				
Screen	1.14 inch full colour screen																				
Buttons	Up, Down, Left, Right, Centre 5 buttons																				
Working Temperature	Charging 0~40 degrees Celsius, Discharging																				
Life Cycles	>300 times																				
Weight	520g																				
Input	Type-C1, DC																				
Output	Type-C1, Type-C2, USB-A, DC																				
Simultaneous charging and discharging	Support, prioritise mobile phone charging																				
Input&Output	<table border="1"> <tr> <td>Input</td> <td>Type-C1: 5V==3A 9V==3A 12V==3A 15V==3A 20V==5A 100W Max DC: 5V==3A 9V==3A 12V==3A 15V==3A 20V==3A 60W(Max)</td> </tr> <tr> <td>Single Port Output</td> <td>TYPE-C1 Output: 5V==3A,9V==3A 12V==3A 15V==3A 20V==5A TYPE-C2 port output: 5V==3A 9V==3A 12V==2.5A 15V==2A 30W(Max) USB-A output: 5V==4.5A 5V==3A 9V==2A 12V==1.5A 22.5W(Max) DC port output: 5V==3A 9V==3A 12V==3A 15V==3A 20V==3.25A 24V==</td> </tr> <tr> <td>Combined output</td> <td>C1+C2: PD65W(20V==3.25A) + PD30W(15V==2A) C1+A: PD65W (20V==3.25A) + SCP22.5W (5V==4.5A) C2+A: 5V==3A(Max) DC+C1: 100W (20V==5A) Priority C1 100W, DC off DC+C2: 65W (20V==3.25A) + PD30W (15V==2A) DC+A: 65W (20V==3.25A) + SCP22.5W (5V==4.5A) DC+(C2+A): 65W(20V==3.25A)+(5V==3A) C1+(C2+A): PD65W(20V==3.25A)+(5V==3A)</td> </tr> </table>	Input	Type-C1: 5V==3A 9V==3A 12V==3A 15V==3A 20V==5A 100W Max DC: 5V==3A 9V==3A 12V==3A 15V==3A 20V==3A 60W(Max)	Single Port Output	TYPE-C1 Output: 5V==3A,9V==3A 12V==3A 15V==3A 20V==5A TYPE-C2 port output: 5V==3A 9V==3A 12V==2.5A 15V==2A 30W(Max) USB-A output: 5V==4.5A 5V==3A 9V==2A 12V==1.5A 22.5W(Max) DC port output: 5V==3A 9V==3A 12V==3A 15V==3A 20V==3.25A 24V==	Combined output	C1+C2: PD65W(20V==3.25A) + PD30W(15V==2A) C1+A: PD65W (20V==3.25A) + SCP22.5W (5V==4.5A) C2+A: 5V==3A(Max) DC+C1: 100W (20V==5A) Priority C1 100W, DC off DC+C2: 65W (20V==3.25A) + PD30W (15V==2A) DC+A: 65W (20V==3.25A) + SCP22.5W (5V==4.5A) DC+(C2+A): 65W(20V==3.25A)+(5V==3A) C1+(C2+A): PD65W(20V==3.25A)+(5V==3A)														
Input	Type-C1: 5V==3A 9V==3A 12V==3A 15V==3A 20V==5A 100W Max DC: 5V==3A 9V==3A 12V==3A 15V==3A 20V==3A 60W(Max)																				
Single Port Output	TYPE-C1 Output: 5V==3A,9V==3A 12V==3A 15V==3A 20V==5A TYPE-C2 port output: 5V==3A 9V==3A 12V==2.5A 15V==2A 30W(Max) USB-A output: 5V==4.5A 5V==3A 9V==2A 12V==1.5A 22.5W(Max) DC port output: 5V==3A 9V==3A 12V==3A 15V==3A 20V==3.25A 24V==																				
Combined output	C1+C2: PD65W(20V==3.25A) + PD30W(15V==2A) C1+A: PD65W (20V==3.25A) + SCP22.5W (5V==4.5A) C2+A: 5V==3A(Max) DC+C1: 100W (20V==5A) Priority C1 100W, DC off DC+C2: 65W (20V==3.25A) + PD30W (15V==2A) DC+A: 65W (20V==3.25A) + SCP22.5W (5V==4.5A) DC+(C2+A): 65W(20V==3.25A)+(5V==3A) C1+(C2+A): PD65W(20V==3.25A)+(5V==3A)																				
Screen	<table border="1"> <tr> <td>Main interface</td> <td></td> <td>Cell Status</td> <td></td> </tr> <tr> <td>-Blue: 81%~100% Capacity -Orange: 31%~80% Capacity -Red: 0%~30% Capacity</td> <td></td> <td>Input Status</td> <td></td> </tr> <tr> <td>Function menu</td> <td></td> <td>Output Status</td> <td></td> </tr> <tr> <td>Temp Setting</td> <td></td> <td>DC Output Settings</td> <td></td> </tr> <tr> <td>Battery Info</td> <td></td> <td>Rest time setting</td> <td></td> </tr> </table>	Main interface		Cell Status		-Blue: 81%~100% Capacity -Orange: 31%~80% Capacity -Red: 0%~30% Capacity		Input Status		Function menu		Output Status		Temp Setting		DC Output Settings		Battery Info		Rest time setting	
Main interface		Cell Status																			
-Blue: 81%~100% Capacity -Orange: 31%~80% Capacity -Red: 0%~30% Capacity		Input Status																			
Function menu		Output Status																			
Temp Setting		DC Output Settings																			
Battery Info		Rest time setting																			
Pushbutton operation	<p>Middle button: push the button to confirm the selection, long press 3S to close the display with</p> <p>Left button: long press 2S to switch between Chinese and English.</p> <p>Up, down, left, right button: push button for direction selection.</p>																				
What's in the box	<table border="1"> <tr> <td>Power Bank *1</td> <td></td> <td></td> <td></td> </tr> <tr> <td>Cable USB-A * 1</td> <td></td> <td></td> <td></td> </tr> <tr> <td>Cable USB-C * 1</td> <td></td> <td></td> <td></td> </tr> <tr> <td>Cable DC * 1</td> <td></td> <td></td> <td></td> </tr> </table>	Power Bank *1				Cable USB-A * 1				Cable USB-C * 1				Cable DC * 1							
Power Bank *1																					
Cable USB-A * 1																					
Cable USB-C * 1																					
Cable DC * 1																					