

Address: Tower B, Qiaode Technology Park, No. 7 Road, Guangming District, Shenzhen, Guangdong Province, China
Customer Service: support@x-sense.com X-SENSE Technology Co., LTD.

CO sensitivity: 50 ppm: 60-90 minutes 100 ppm: 10-40 minutes 300 ppm: 0-3 minutes
Standby mode: The LED indicator will flash green once every 60 seconds. **Smoke alarm:** 3 long beeps every 1.5 seconds. The LED indicator will flash red with the alarm sound. **CO alarm:** 4 quick beeps every 5.8 seconds for the first 4 minutes. After 4 minutes, 4 quick beeps every 60 seconds. The LED indicator will flash red with the alarm sound. **Low battery:** The LED indicator will flash yellow with 1 beep every 60 seconds. **Fault:** The alarm will deliver 2 beeps approximately every 40 seconds and the LED indicator will flash yellow 1-4 times. **Silence mode:** Silence time of around 9 minutes. The LED indicator will flash red once every 5 seconds. **Maintenance:** Test weekly by pushing the TEST/SILENCE button twice. Clean the alarm cover and vents with a soft brush once a month to remove dust and dirt.
CAUTION: READ THESE INSTRUCTIONS CAREFULLY BEFORE OPERATING OR SERVICING.

Batch Number:

B2B20210616001

X-SENSE

Combination Smoke and Carbon Monoxide Alarm

Model: SC01 (10-Year Sealed Lithium Battery)



2797-CPR-693083 KM 692995

EN 14604:2005

EN 50291-1:2010

Do not locate the alarm in areas where the temperature is below 4.4 °C (40 °F) or above 37.8 °C (100 °F), or in areas where the humidity is higher than 85%. **CONSTANT EXPOSURE TO HIGH OR LOW TEMPERATURES OR HIGH HUMIDITY MAY REDUCE THE BATTERY LIFE.** After the unit is fully mounted into the mounting bracket, it will be automatically activated. **The battery is not replaceable.**

This unit comes with a 10-year sealed lithium battery without any user serviceable parts inside. See the user manual for complete instruction. Weekly test is required. Replace the unit within 10 years of installation date.

WARNING:

Once the maximum lifetime (10 years) is reached, the alarm will deliver 2 beeps every 30 seconds. 1. Pressing the TEST/SILENCE button can silence the end-of-life signal for up to 3 days. 2. When the unit is at the end of its life, deactivate it before disposing. 3. **Do not deactivate** the alarm unit until the end-of-life signal has been heard. Once the alarm is deactivated, it will no longer function. It cannot be reactivated and must be replaced.

To deactivate: 1. Peel back the shaded label obstructing the "DIS" setting, and break the thin plastic guard, as below. 2. Twist the plastic pin upwards to the "DIS" position or insert a screwdriver into the slot and turn the dial clockwise to the "DIS" position to deactivate. 3. Dispose of the alarm. 4. Replace the alarm.

Peel back the label obstructing the "DIS" setting as below, then move the plastic pin upwards to deactivate the unit.



MADE IN CHINA SC01-7204 V00

Software version: 1.045