



### COMBO130

Mixer/amplifier/multimedia player combo

- All-in-one system
- 5-input mixer
- Chime with pushbutton
- Mountable in 19" wide racks
- 70 V/100 V or low impedance amplified output



---

SKU: H9750

Categories: [Multimedia players](#), [Amplifiers](#), [Audio mixers](#)

### FEATURES

- All-in-one 130W system
  - 5-input mixer:
    - 3 mic channels – Aux1/MP3/TUNER – Aux2
      - Bass and treble settings
    - MP3 player and tuner control
      - Chime activation
    - Output volume on VU metre
  - 6.35mm jack inputs for mics 1 and 2
    - RCA input for AUX1 and AUX2
      - RCA output
    - AM/FM antenna connectors
  - 100V/16 to 4 ohms outputs on terminal block
    - Tuner: AM/FM
      - Autoscan, manual scan
    - FM frequency range: 87.5MHz – 108MHz
    - AM frequency range: 522kHz – 1,620kHz
      - USB reader: mp3 files
- Features: playback, search, range programming

- Power supply: 220V 50-60Hz
- Power consumption: 175W
- Dimensions: 483 x 89 x 366 mm
  - Net weight: 11.36kg