

Address: B4-503, Kexing Science Park, 15 Keyuan Road, Shenzhen, 518057, CHINA
Email: support@x-sense.com X-Sense Innovations Co., Ltd.



CO sensitivity: 30 ppm: over 120 minutes; 50 ppm: 60–90 minutes; 100 ppm: 10–40 minutes; 300 ppm: 0–3 minutes. **Standby mode:** The LED indicator will flash green once every 60 seconds.

Smoke alarm: 3 long beeps every 4 seconds. The LED indicator will flash red with the alarm sound. **CO alarm:** 4 quick beeps every 5.8 seconds. The LED indicator will flash red with the alarm sound. **Low battery:** The LED indicator will flash yellow with 1 beep every 60 seconds. **Fault:** The alarm will deliver 2 beeps and the LED indicator will flash yellow 2 times every 60 seconds. **Silence mode:** Silence time of around 9 minutes. The silence mode silences the audible alarm only. The LED flashing will not be suppressed. **Maintenance:** Test weekly by pushing the TEST/SILENCE button. Clean the alarm cover and vents with a soft brush once a month to remove dust and dirt.

Batch Number:

ZN023030602NT

X-SENSE

Combination Smoke and Carbon Monoxide Alarm (Type B)

Model: SC07 (10-Year Sealed Lithium Battery DC 3.0 V)



Do not locate the alarm in areas where the temperature is below 4.4°C (40°F) or above 37.8°C (100°F), or in areas where the humidity is higher than 85% or lower than 10%, as this may reduce the battery life. **CONSTANT EXPOSURE TO HIGH OR LOW TEMPERATURES OR HIGH HUMIDITY MAY REDUCE THE BATTERY LIFE.** After the unit is fully mounted into the mounting bracket, it will be automatically activated. **The battery is not replaceable.**

This unit comes with a 10-year sealed lithium battery without any user serviceable parts inside. See the user manual for instructions. Weekly test is required. Replace the unit within 10 years of installation date.

⚠ WARNING:

Once the maximum lifetime (10 years) is reached, the alarm will deliver 3 beeps every 60 seconds. This end-of-life signal can be temporarily silenced for 22 hours by pressing the TEST/SILENCE button. When the unit is at the end of its life, deactivate it before disposing. **Do not deactivate the alarm unit until the end-of-life signal has been heard. Once the alarm is deactivated, it will no longer function. It cannot be reactivated and must be replaced.**

To deactivate: 1. Peel back the shaded label obstructing the "DIS" setting, and break the thin plastic guard, as below. 2. Twist the plastic pin upwards to the "DIS" position or insert a screwdriver into the slot and turn the dial clockwise to the "DIS" position to deactivate the unit. 3. Dispose of the alarm. 4. Replace the alarm (Pressing the TEST/SILENCE button can silence the end-of-life signal for up to 3 days).

Peel back the label obstructing the "DIS" setting as below, then move the plastic pin upwards to deactivate the unit.



DEACTIVATE
ON



EN 14604:2005+AC:2008

EN 50291-1:2018

MADE IN CHINA

1008-CPR-MC 69266137 0001

F.2.01.SC0706 V00