

SMART PROTECT PLUS BANKNOTE DETECTOR

ratio tec[®]
get connected



The Smart Protect Plus is part of the new generation of our automatic banknote detectors - in a fresh, modern design and with improved test sensors. With the help of the Smart Protect Plus, banknotes can be clearly verified directly at the POS in less than a second. Suspicious banknotes are indicated by means of the the LED-bar, the LCD and an acoustic warning signal and are ejected separately. The detector with automatic currency recognition also has a counting function and can determine the quantity and total amount of the tested banknotes.

- Compact banknote detector – ideal for the POS
- Currencies: EUR | GBP | CHF
- Automatic currency recognition
- 100% reliable detection of counterfeits* in less than a second
- Counterfeit detection:
IR | MG | MT | SD | WM | TD | Colour
- Future-proof thanks to improved sensors (IR & MG)
- Clear result due to acoustic warning signal, LED-bar, LCD and banknote ejection (suspicious banknotes at the front or back)
- High-quality and clear display
- Simple and intuitive operation
- Easy to open and easy to clean
- Displays the total amount and quantity of the accepted banknotes counted
- New updates via Update Manager (via USB cable) or microSD-card



Green LED-bar:
genuine banknote



Red LED-bar:
suspicious banknote



Easy-to-open construction for an unproblematic cleaning and maintenance of the device.

Technical data	Smart Protect Plus
Currency	EUR GBP CHF
Counterfeit detection	IR MG MT SD WM TD Colour
Counting function	✓
Report function	✓
Standby mode (ECO)	✓
Acoustic warning signal	✓ ON OFF
Banknote ejection	Front or back suspicious banknote separately
Display	LED-bar/LCD
Possible to open	✓
Speed per banknote	< 0,5 seconds
Update	Update Manager microSD-card
Accessories	Rechargeable battery cleaning set
Contents	Mains cable user manual
Measurements (l x w x h in mm)	137 x 117 x 62
Weight (in kg)	0.5

* This product has been successfully tested.
<http://www.ecb.europa.eu/euro/cashprof/cashhand/devices/html/results.en.html>

www.ratio-tec.com