



# Instruction of Assembly

## 8 petals of FX#1



1, open the box and take out all the components



2, place all the components on a clean and flat table



3, find out the 4 petals with closed holes as shown, and assemble 2 short tubes to each, the short threaded end of the tubes goes into the petals



4, assemble the 2 short tubes to 2 petals, the short threaded end of the tubes goes into the petals



5, assemble the long tubes to the rest 2 petals, the short threaded end of the tubes goes into the petals



6, assemble the 4 petals from step 3 to the four corners of the plate, fix with nuts as shown



7, assemble the 2 petals from step 4 to the middle of the plate



8, assemble the rest 2 petals with long tubes to the plate as shown



9, assemble flat-headed screws to the hanger with nuts in, but don't lock up yet



10, put down the hanger, make sure all the screws can go through the four small holes at the plate, then take it out and fasten the nuts



11, connect the wires of each petal to the collector











12, install the hanger to the ceiling with sharp pointed screws using a electric drill do not move the flat-headed screws



13, lift up the light and install it to the hanger, the four flat-headed screws go through the plate, and fasten with the nuts as shown

## Accessories

			
Drive	Wrench	Cross	Nuts
			
Screws	Tubes	User Manual	Remote

Actual shapes or quantities depends on specific orders

## Remote pairing



Step 1,  
put batteries in the remote



Step 2,  
turn on the light and press the "ON/OFF" button immediately,  
the light flashes three times and the pairing is done

## APP pairing



app and install in phone



Step 2,  
turn on the light, press the ON in  
the APP immediately, then the  
pairing starts



Step 3,  
after the pairing, the light can be  
controlled by the phone as shown