



hoco.

PD20W  
Small  
body

hoco.accessory

MINI  
Small and powerful

PD  
20W

66%

**EN:**  
Input: AC100-240V 50/60Hz 0.3A Max  
Output: Type-C: 5.0V~3.5A 5.0V~2.25A  
12.0V~1.67A (20.25W max)  
PPS: 3.3-11.2V~1.8A (20.25W max)  
Maximum output: 20.25W Max

**DE:**  
Eingang: AC100-240V 50/60Hz 0.3A max  
Ausgang: Type-C: 5.0V~3.5A 5.0V~2.25A  
12.0V~1.67A (20.25W max)  
PPS: 3.3-11.2V~1.8A (20.25W max)  
Maximale Leistung: 20.25W max

**PL:**  
Wzrostak: AC100-240V 50/60Hz 0.3A maks  
Wyjscie: Type-C: 5.0V~3.5A 5.0V~2.25A  
12.0V~1.67A (20.25W maks)  
PPS: 3.3-11.2V~1.8A (20.25W maks)  
Maksymalna moc wyjsciowa: 20.25W maks

**ES:**  
Entrada: AC100-240V 50/60Hz 0.3A máx  
Salida: Type-C: 5.0V~3.5A 5.0V~2.25A  
12.0V~1.67A (20.25W máx)  
PPS: 3.3-11.2V~1.8A (20.25W máx)  
Salida máxima: 20.25W máx

**FR:**  
Entrée: AC100-240V 50/60Hz 0.3A max  
Sortie: Type-C: 5.0V~3.5A 5.0V~2.25A  
12.0V~1.67A (20.25W max)  
PPS: 3.3-11.2V~1.8A (20.25W max)  
Puissance maximale: 20.25W max

**RU:**  
Вход: AC100-240V 50/60Hz 0.3A макс  
Выход: Type-C: 5.0V~3.5A 5.0V~2.25A  
12.0V~1.67A (20.25W макс)  
PPS: 3.3-11.2V~1.8A (20.25W макс)  
Максимальная мощность: 20.25W макс

**AR:**  
Entrada: AC100-240V 50/60Hz 0.3A max  
Salida: Type-C: 5.0V~3.5A 5.0V~2.25A  
12.0V~1.67A (20.25W max)  
PPS: 3.3-11.2V~1.8A (20.25W max)  
Potencia máxima disponible: 20.25W max

**IT:**  
Ingresso: AC100-240V 50/60Hz 0.3A max  
Uscita: Type-C: 5.0V~3.5A 5.0V~2.25A  
12.0V~1.67A (20.25W max)  
PPS: 3.3-11.2V~1.8A (20.25W max)  
Potenza massima erogabile: 20.25W max

**Ab:**  
تدخل: AC100-240V 50/60Hz 0.3A  
مخرج: Type-C: 5.0V~3.5A 5.0V~2.25A  
12.0V~1.67A (20.25W Max)  
قد توفر قوة 20.25 وات كحد أقصى

品牌: hoco. 浩酷  
 制造商: 深圳浩酷科技发展有限公司  
 地址: 深圳市宝安区龙华街道清华社区海龙  
 大道2125号卫尔龙商务大厦A栋408  
 网址: www.hocotech.com  
 服务热线: 400-6515-153  
 执行标准: Q/HOCO 007-2017



N27 创新单口PD20W充电器 黑色(EU)  
 N27 Innovative single port PD20W charger(EU)  
 black



Standard: HPQS-22/a  
 22/09/SLVAQXW



Don't disassemble in case of electric shock!  
 Please use in a dry environment!