



## Silvergear Silent Disco Set 3945 USER MANUAL

### What's in the box:

- 5 rechargeable Silent Disco headphones
- 1 wireless and high quality Silent Disco transmitter
- Mini-USB charging cables for 5 headphones
- 3.5mm audio cable and adapter to RCA

Fig A



Fig A:

- 1.CHANNEL: This switch changes the channel the transmitter is using. Press to switch between channel 1, 2, 3, etc.  
Notes: When more than two transmitters are working simultaneously, make sure each transmitter on a different channel.
- 2.AUDIO INPUT: Connect your mixer or audio device to the AUDIO INPUT. Notes: Blue LED lights will display when the audio is playing on the music device to show it's connected.
- 3.DC-12V: Connect the power adapter here to power the transmitter.  
Notes: The light will illuminate blue when the transmitter powers on.

1

### Getting Connected

- 1.Connect to a variety of audio devices, e.g. mobile phone, tablet, or DJ equipment using the 3.5mm jack input.
- 2.Select from one of the available frequencies to broadcast on with the Channel Select switch.

### Headphone Operation:

- 1.POWER/TUNE: Hold the power button for ~3 seconds to turn the headphones on and off.  
Press the power button once to change the selected channel. The LED lights will change to display the currently selected channel.  
Channel 1- Red  
Channel 2- Green  
Channel 3- Blue
- 2.VOLUME/LED: Push the volume key up or down to adjust volume.  
Press the volume switch in and hold for ~2 seconds to toggle the LED light mode. LED will toggle between always on, off and blink.

### Charging The Headphone:

The rechargeable headphone has a 600mAh 3.7v Lithium Ion Battery and are rechargeable via a mini-USB connection with the supplied charging cables that fit any standard USB charger. The headphones are fully charged again within 4 hours.

2

### Features of headphone:

- Transmit audio to a range of up to 100 meters in optimal areas.
- Active noise reduction system for crystal clear sound.
- The advanced 40 mm speakers provide a well-balanced high-definition sound.
- Double PLL system for ultimate frequency stability.
- Big channel-indicating logo light, you can see the channel difference by logo color change.
- Soft leatherette ear cushions and robust headband let you listen to your entertainment in extreme comfort, even during long hours of extended wear.
- Endless headphones can be used simultaneously with one transmitter.
- The headphones automatically turn off after 5 minutes of no broadcast audio, so you never have to think about it and you'll never be left with an empty battery.

### Troubleshooting:

Why am I not hearing any sound from the headphone receiver(s)?

- Make sure the headphone receivers are tuned to the same channel as the transmitter.
- Double check the volume levels at:  
Music source  
Any sound equipment connected to the transmitter  
Headphone receiver(s)
- Double check the connections from the Music Source to the Audio Input.
- Ensure the internal batteries are fully charged for the headphones.

3

### Technical specifications headphones:

System	UHF/RF
Modulation	FM
Audio Mode	Stereo
Effective range	100M
Speaker	40mm mylar
Impedance	32 ohm
Frequency Response	30~15,000Hz
S/N Ratio	≥75dB
Channel separation	>40dB
Distortion:	<1%
Power supply of headphone	Grade-A 600mAh Built-in lithium battery (work time: about 8 hours)

### Technical Specifications Transmitter:

Modulation:	FM
Voltage:	12VDC
Current:	130mA
Frequency:	863Mhz
Effective Work Distance:	100M
Power:	10 dbm
Power adapter:	12v, 130mA
Audio cables:	3.5mm Jack ( m ) to 3.5 mm Jack ( m ) cable 3.5 mm Jack ( f ) to RCA ( m ) cable

4

### Entsorgung

Entsorgen Sie den Artikel und das dazugehörige Verpackungsmaterial gemäß den geltenden örtlichen Vorschriften.

### Abfallentsorgung und Abfallsammlung:

Elektronische und elektrische Geräte dürfen nach Europäischem Recht nicht im Hausmüll entsorgt werden. Deren Bestandteile müssen getrennt der Wiederverwertung oder Entsorgung zugeführt werden, da bei unsachgemäßer Entsorgung gefährliche und giftige Bestandteile in die Umwelt gelangen und diese nachhaltig schädigen können. Als Verbraucher sind Sie nach dem Elektrogesetz (ElektroG) verpflichtet, elektrische und elektronische Geräte am Ende ihrer Lebensdauer an den Hersteller, die Verkaufsstelle oder an dafür eingerichtete, öffentliche Sammelstellen kostenlos abzugeben. Genau Einzelheiten hierzu regelt das jeweilige Landesrecht.

Itemnumber: 3945  
Batchnumber: 23729  
Name and address:  
Karsten International B.V.  
Overschiestraat 63  
1062 XD Amsterdam  
The Netherlands

Made in China

silvergear.eu



Raccolta carta  
Verifica le disposizioni

