



I. Installeer de FindmyTag app

Klik om te installeren



Geschied voor Android met NFC functie en Apple telefoons vanaf iPhone 7

Scan de QR code om de app te installeren



U kunt de app ook zoeken in de Google Play Store en Apple App Store: FindmyTag

www.findmytag.online

II. Opstarten en batterij vervangen



Verwijder label om de tag op te starten

Een 'bleep' geluid bevestigt het succesvol opstarten van de tag. Open de FindmyTag en druk op het plusje (+) om een nieuwe tag te koppelen. Geef uw tag een naam en voer uw telefoonnummer of emailadres in om uw tag te activeren.



Demonteer behuizing van de tag om de batterij te vervangen. Sluit de tag na het vervangen van de batterij. De tag zal 3 keer een 'bleep' geluid afspelen bij activatie.

III. Functionaliteiten app

Speel geluid af: Het geluidssymbool zal oplichten, wanneer de tag dichtbij is (binnen 10 meter). De tag speelt 3 keer een 'bleep' geluid af door te klikken op het geluidssymbool in de app.

Vinden op de kaart: Wanneer de tag ver van u verwijderd is, kunt u hem terugvinden op de kaart in de app. De tag zendt een beveiligd bluetooth signaal uit, dat kan worden opgepakt door miljoenen smartphones en tablets overal ter wereld. Deze sturen vervolgens de locatie van de tag door naar de app.

Disclaimer: De developers zijn continu bezig met het doorontwikkelen van de app, maar kunnen geen stabiele netwerkverbinding garanderen. Wij behouden ons het recht voor toekomstige modificaties van hardware en software.

IV. Specificaties en garantie

MCU	ARM 32-bit processor, Bluetooth low energy built-in
NFC	<input checked="" type="checkbox"/> ISO14443A, NFC Forum Type 2 Tag
Sensor	<input checked="" type="checkbox"/> 3-Axis accelerometer motion sensor
Reminder	<input checked="" type="checkbox"/> Buzzer <input checked="" type="checkbox"/> LED
Battery Capacity	220mAh, CR2032
Phone OS	Support Bluetooth 4.0/Android 4.4/iOS 9.0 Above
Protection Class	<input checked="" type="checkbox"/> IP65 <input type="checkbox"/> IP67

Eén jaar garantie op de tag. Waterschade en het zelf openen van de tag en PCBA is uitgesloten van garantie.


I. Install app & Retrieve Key

Tap to Install




Android with NFC function and iPhone 7 and above model.

Scan to Install (Use native Browser)



Use Retrieve Key for re-installing App. Please keep the key for future use.

II. Power up & Replace Battery



Pull out to Power up


A 'beep' sound shows power up successfully. Open the app, phone will find the new tag, select the name and enter your phone or email to activate the tag.



Battery cover

Lever the tag cover to replace the battery. Tag will play three 'beep' sounds if activated.

III. App Operation & Thanks

Beep Nearby: When tag is nearby (within 10 meters), the beep icon will be lighted, press the Beep button  will make the tag beep twice or more.

Find on Map: When the tag is far away from you, try to find on map. If somebody else find your tag, his phone will transmit the SN and the location to server, then you may get a report and decrypt the data by your phone, so you will get the location of your Tag (not real-time updating).

Disclaimer: The product team will continue to improve the experience, but we can not promise you a reliable network location. We reserve the right for further modification of hardware and software.

IV. Specification & Warranty

MCU	ARM 32-bit processor, Bluetooth low energy built-in
NFC	<input checked="" type="checkbox"/> ISO14443A, NFC Forum Type 2 Tag
Sensor	<input checked="" type="checkbox"/> 3-Axis accelerometer motion sensor
Reminder	<input checked="" type="checkbox"/> Buzzer <input checked="" type="checkbox"/> LED
Battery Capacity	220mAh, CR2032
Phone OS	Support Bluetooth 4.0/Android 4.4/iOS 9.0 Above
Protection Class	<input checked="" type="checkbox"/> IP65 <input type="checkbox"/> IP67

One year warranty for the Tag device, except water inflow or opening the device and the PCBA by yourself. The attached complimentary parts are without guarantee.