

X-SENSE | Link+Pro

X-Sense Electronics Co., Ltd.

Link+Pro Smoke Alarm with Voice and Location

Model: XS0B-MR

Band: 869.25-869.3 MHz

Max. RF Power: 10 mW

Input: 3 V DC

Battery Type: CR123A lithium battery × 1

Test weekly. The green LED flashes once every 60 seconds, indicating proper operation. Please read the user manual carefully before installing and/or operating.

Location Button

WARNING - Test the alarm for correct operation using the test facility, whenever the battery is replaced.

USE ONLY CR123A LITHIUM BATTERIES WITH THIS DEVICE. OTHER TYPES OF BATTERIES MAY DAMAGE IT.

WARNING: Do not locate the alarm in areas where the temperature is below 40°F (4.4°C) or above 100°F (37.8°C), or in areas where the humidity is higher than 85% or lower than 10%, as this may reduce the battery life. CONSTANT EXPOSURE TO HIGH OR LOW TEMPERATURE OR HIGH HUMIDITY MAY REDUCE THE BATTERY LIFE.

IMPORTANT: Once the maximum lifetime (10 years) is reached, the alarm will deliver 3 beeps every 60 seconds. This end-of-life signal can be temporarily silenced for 22 hours by pressing the TEST/SILENCE button.

Batch Number: ZN024091401NT MADE IN CHINA UK

