

# PROFESSIONAL 22 Amp 12 V BATTERY CHARGER N/E AmpM SH 180



(picture for illustration purposes only)



|                     |   |                     |                     |
|---------------------|---|---------------------|---------------------|
| Voltage             | 12 Volt   | Case                | Steel               |
| Load current        | 22 Amps   | Indicator of charge | Ammeters            |
| Load type           | Standard  | Switch              | Low /High           |
| JumpStarter         | 180 Amps  | Norm                | CE, ROHS.           |
| Capacity of battery | 30 - 225Ah<br>Low: 30 - 160 Ah<br>High: 50 - 225 Ah | Display             | Symbol              |
| Battery type        | Lead/ AGM   | Size                | 36,5 x 18 x 22,5 cm |
|                     |   | Weight              | 9 kg                |

**Technical description**  
Standard charger requiring manual disconnection after charging. JumpStarter: 180 Amps ; very fast charging less 15min. Possibility to select Low or High charging process. Metal housing with a strong spray coating.  
Circuit breaker  
Handles

**Item reference** 0242201110-2020  
**EAN Code** 4002031220293  
**Packaging** Description in German, English, French, Italian, Spanish, Dutch.

**Instruction manual** German, English, French, Italian, Spanish, Dutch.  
**Manufacturing** RPC  
**From** Luxemburg  
**Design and quality** Germany  
**Warranty & service** 2 years, back to the dealer to repair, change or credit note.



MSA International S.A. //  
ABSAAR®  
www.msainternational.com  
www.absaar.com  
T: 00352 26 65 65 1  
M: info@absaar.com

ZAE Robert Steichen  
5, rue Bommel  
L-4940 Hautcharage  
Luxembourg

