



# ET 50150 R

**Self monitoring electronic transformer**  
Dimmable with resistive AND inductive dimmers Round dimmable

### LED functions

- On: normal operation
- Off: out of order (check main power)
- Slow flashing: short circuit condition
- Rapid flashing: transformer overload

50-150 W/VA  
Pri: 220-240V~50/60Hz 0.62A  
Sec: 11.4V~eff, 13A ta: 45°C  
Cos  $\phi$ =0.98 tc: 80°C

