

WIRELESS RECEIVER

* FEATURES

Device name: Wireless receiver
Call number: support
Voice prompt: support
Chinese and English dual voice: support (default English)
Drag two: support
Pairing timeout shutdown: pairing state lasts 5 minutes after shutdown
Low voltage reminder: when the voltage is less than 3.2V reminder, every 5 seconds to remind 1 times, 3.1V shutdown

* System state

Power off: MFB long by 3 seconds
Volume plus: short press VOL+
Volume reduction: short press VOL-
Toggle language: double click on the pairing state (red and blue lights on flash) to hold down MFB

* Telephone control

Answer the phone: call by MFB
Refused to answer the phone calls: long press MFB
No number redial: double-click the MFB button, then press MFB to cancel out short

* LED light display

Boot pairing: red and blue lights flash alternately
Connection status: blue light slow flash (5 seconds 1)
Low voltage: red light flash (0.5 sec. 1)

* Music control

Play pause: press MFB
Last one: VOL- long press 2 seconds
Next: VOL+ long press 2 seconds

* Operating current

State parameter (4.00V) parameter (3.40V)
Rated voltage 4.00V 3.40V
Paired state current 4.33mA-20.56mA
4.47mA-22.03mA
Standby current (connected Wireless)
0.43mA-8.31mA 0.41mA-8.74mA
Play music current 19.04mA-23.21mA.
22.85mA-23.74mA
Talk current 23.82mA-24.05mA
25.19mA-25.78mA
Charging current 100.0mA. 100.0mA
Shutdown current 1.4uA 1.1uA



MADE IN CHINA